

APPENDIX #3

APPENDIX #3 – RS-232 Protocol

- 1) Use PC keyboard to simulate DVR keypad.
- 2) Data: REMOTE PROTOCOL use 8 bit data, 1 start bit, 1 stop bit.
- 3) Command Protocol: 0XFF 0XC0 ID Function 0x7F

FUNCTION	CODE	ASCII	FUNCTION	CODE	ASCCI
KEY_MENU	0x4D	M	KEY_CH1	0x31	1
KEY_ENTER	0x0D	ENTER	KEY_CH2	0x32	2
KEY_4 CUT	0x61	a	KEY_CH3	0x33	3
KEY_ZOOM	0x5A	Z	KEY_CH4	0x34	4
KEY_9 CUT	0x62	b	KEY_CH5	0x35	5
KEY_16 CUT	0x63	c	KEY_CH6	0x36	6
KEY_SLOW	0x53	S	KEY_CH7	0x37	7
KEY_REC	0x72	r	KEY_CH8	0x38	8
KEY_LEFT	0x4C	L	KEY_CH9	0x39	9
KEY_UP	0x55	U	KEY_CH10	0x41	A
KEY_PLAY	0x50	P	KEY_CH11	0x42	B
KEY_DOWN	0x4E	N	KEY_CH12	0x43	C
KEY_RIGHT	0x52	R	KEY_CH13	0x44	D
KEY_POWER	0x57	W	KEY_CH14	0x45	E
KEY_KEY LOCK	0x4B	K	KEY_CH15	0x46	F
			KEY_CH16	0x47	G